

Kentix SmartRelay (KXP-2-RS)

PDF-Export



TYP: KXP-2-RS	SmartRelay for connecting wall readers (type: KXC-WAx-IPx) or for SmartAccess-GO
Connection option	Stand-alone or in combination with other AlarmManagers
Number of doors	Up to 2 doors with 4 readers
Networking	Up to 999 AccessManagers can be networked in master-slave mode Management via the Master AccessManager
Interner Speicher	5.000 persons - access credentials 100 door profiles 100 time profiles (day, week)
SD card	Integrated Micro SD card holder up to 128 GB
Buzzer	85dB, 2.3kHz
LED	ALARM (red), RUN (green), LINK/ACT to LAN socket
LAN (PoE)	10/100 Mbit LAN Anschluss mit PoE, Integrierter Web-Server Ports: 443 TCP (HTTPS), 5222 TCP (Kentix360), 161 UDP (SNMP-GET), 162 UDP (SNMP-TRAP)
Power supply (PoE)	PoE class 3, power consumption in operation approx. 3W with splitter function max. 15W short-term
Integrated PoE splitter	24VDC/500mA (max. 1A/250ms)
Relay for door-strike	2pc. relay: 125VAC/60VDC, 1A, changeover contact, cable diameter: 0,205 - 1,31 mm ²
Size	47 x 48 x 33 mm WxHxD, installation in switch box or on DIN rail
Connection wall-reader	4-wire, length up to 500m, up to two wall or fingerprint readers can be connected, up to 16 DoorLock-RA4 can be connected
Environmental conditions	0°C bis +60°C, non condensing
Protection class	IP20
Configuration-Software	Integrated web-server (HTTP/HTTPS)
Content of delivery	Kentix SmartRelay, mounting material
Accessories	Wall-reader types (KXC-WA2-IP1, KXC-WA3-IP1, KXC-WA4-IP1, KXC-WA5-IP1) PoE injector (KPOE150S)
Prüfungen	CE