

PowerManager (KPM-RF-B) - LEGACY

PDF-Export



Connectivity	Stand-Alone operation or Master-Slave network Integrated web server (HTTPS, Port 443)
Management	HTTPS (certificate), integrated web server, ReSt-API Port security 802.1x Protocols: SNMP V2/3 (GET, TRAP), NTP, SMTP, DHCP
Connection radio meters	Up to 25 wireless meters (ZigBee)
Connection RS485 meters	Up to 32 RS485 (ModBus RTU) meters
Connection Ethernet meters	Up to 100 Ethernet (Modbus IP) meters
Internal Signal	85dB, 2.3kHz
LED	RUN (green/red), LINK/ACT on LAN Port
Ethernet	10/100 Mbps LAN Port with PoE
Voltage supply (PoE)	PoE Class 1, power consumption approx. 2W
External memory	Micro SD card up to 128GB
Radio	ZigBee 2,4 GHz, encoding AES 128 Bit, radio module can be switched off reach up to approx. 25m depending on building structure and environment
KENTIX system port	RJ45, for connecting external Kentix Plug'n Play Modules (KIO3) for ModBus meters
Chassis	Material: PS 90 x 90 x 45 mm Weight: ca. 100g Color: Black, Protection IP20
Environmental conditions	Temperature 0 to 50°C, Humidity 5-95%, not condensing
Types	KPM-RF-B (Chassis Black)
Delivery	Mounting bracket, mounting material
Accessories	PoE Injector (KPOE150S) Power Adapter (KIO3) to connect external outputs, ModBus RS485 19" mounting bracket (KDA01)
Approvals	CE