

AccessManager for cable readers - DATA SHEET



ORDER-CODES:

KXP-2-RS

| | |
|----------------------------------|--|
| Integrated software | KentixONE via integrated web server (HTTPS) |
| Operation | Stand-alone or networked |
| Number of doors | 2 doors (up to 4 readers inside/outside) |
| Networking | Any number of AccessManagers as main satellite |
| SD card | Integrated Micro SD card holder up to 128 GB |
| Acoustic signal generator | 85dB, 2.3kHz |
| LED | ALARM (red), RUN (green), LINK/ACT to LAN socket |
| Button | Reset button |

| | |
|--|--|
| Network (PoE) | 10/100 Mbit Ethernet port with PoE |
| Power supply (PoE) | PoE class 3, power consumption in operation approx. 3W with splitter function max. 15W short term. |
| Integrated PoE splitter | Voltage output 24VDC/500mA (max. 1A/250ms) for connection of reader and door opener |
| Connection electric strike/lock | 2x relay: 125VAC/60W, 60VDC/30W, 1A, changeover contact (NO/NC) switchable, connection cable thickness: 0.205 - 1.31 mm ² |
| Digital inputs | 2x Digital inputs, each door configurable as: - Alarm input (door open monitoring) - Pushbutton input for door opening |
| RFID reader connection | 4-wire cable (cable: J-Y(ST)Y, 4x2x0.8), cable length up to 500m, up to four readers connectable or up to 16 rack levers (DoorLock-RA4) connectable (cable CAT5/6/7 AWG24) |
| Dimensions | 47 x 48 x 33 mm WxHxD |
| Environmental conditions | Temperature 0 to 60°C, humidity 5-95%, non-condensing |
| Protection class | IP20 |
| Mounting | - On mounting rail / top-hat rail (35mm) - In switch box 60mm |
| IP Ports | - 443 TCP (HTTPS) - 5222 TCP (KentixONE-GO) - 161 UDP (SNMP-GET) - 162 UDP (SNMP-TRAP) |
| Scope of delivery | AccessManager, mounting material, SlimLine cable 3m |
| Accessories | PoE Injector (KPOE150S) |
| Certification | CE, FCC |