



ORDER-CODES:

KXC-WA5-IP2

<b>Function</b>	Biometric wall reader for surface mounting and 2-factor verification
<b>Connection possibility</b>	DoorLock AccessManager (ART: <a href="#">KXP-2-RS</a> )
<b>Configuration</b>	About KentixONE
<b>RFID Reader 13.56MHz</b>	MIFARE® DESFire® MIFARE® Classic, LEGIC prime
<b>Dimensions</b>	88 x 123 x 55 mm WxHxD
<b>LED</b>	RED, GREEN
<b>Acoustic signal generator</b>	80dB, 2.3kHz
<b>Connection of wall reader to AccessManager</b>	4-wire cable (cable: J-Y(ST)Y, 4x2x0.8) Cable length up to max. 500m

<b>Addressing Terminating resistor</b>	<p>Coding switch (default address: 1)            ASSIGNMENT DIP 1:            (1) <b>ADDRESS 1(ON/OFF)</b>            (2) ADDRESS 2 (<b>ON/OFF</b>)            (3) -            (4) -            (5) -            (6) BAUD RATE(<b>ON</b>)            (7) BAUD RATE(<b>OFF</b>)            (8) TERMINATING RESISTOR (<b>ON/OFF</b>)</p> <p>ASSIGNMENT DIP 2:            (1) TERMINATING RESISTOR (<b>ON/OFF</b>)            (2) -</p>
<b>Communication</b>	2-wire RS485, encrypted (AES128)
<b>Environment</b>	Temperature -10°C to +55°C
<b>Power supply</b>	10-30VDC, power consumption 1.9W
<b>Connection</b>	<p>5-pole terminal block detachable            MOVEMENT:            (1) 10-30VDC            (2) GND            (3) DATA-A            (4) DATA-B            (5) -</p>
<b>Protection class</b>	IP54
<b>Scope of delivery</b>	Wall reader
<b>Exams</b>	CE