

## DoorLock-WA2 - DATASHEET



## ORDER-CODES: KXC-WA2-IP2

Function	Wall reader with PIN keypad for mounting in switch box
<b>Connection possibility</b>	DoorLock AccessManager (ART: <u>KXP-2-RS</u> )
Configuration	About KentixONE



RFID Reader 13.56MHz	MIFARE® DESFire® MIFARE® Classic, LEGIC prime LEGIC advant, ISO14443A (CSN / UID) ISO15693 (CSN / UID) Sony FeliCa (CSN / UID) Inside Secure (CSN / UID)
PIN keypad	Touch PIN keypad with function keys for switching the alarm zone "armed (C)/disarmed (E)".
Dimensions	$55 \times 55 \times 6$ mm (dimensions button) $70 \times 70 \times 8$ mm (dimensions with board) Mounting on switch programs with frame cutout $55 \times 55$ mm
LED	RED, GREEN, YELLOW
Acoustic signal generator	80dB, 2.3kHz
Connection of wall reader to AccessManager	4-wire cable (cable: J-Y(ST)Y, 4x2x0.8) Cable length up to max. 500m
Addressing Terminating resistor	Coding switch (default address: 1) MOVEMENT: (1) ADDRESS 1(ON/OFF) (2) ADDRESS 2 (ON/OFF) (3) - (4) - (5) BAUD RATE(ON) (6) - (7) - (8) TERMINATING RESISTOR (ON/OFF)
Communication	2-wire RS485, encrypted (AES128)
Surroundings	Temperature 0°C to +60°C, non-condensing
Power supply	10-30VDC, power consumption 1.9W
Connection	9-pole terminal block detachable MOVEMENT: (1) - (2) - (3) - (4) - (5) - (6) DATA-A (7) DATA-B (8) 10-30VDC (9) GND
<b>Protection class</b>	IP20
Scope of delivery	Wall reader with PIN keypad



Exams	CE