DoorLock-WA2-V2 – Datasheet



ORDER-CODES:
KXC-WA2-IP1-V2, KXC-WA2-IP2-V2

Function	Wandleser mit Kunststoffrahmen zur Unterputzmontage in Standard 60mm Schalterdose
Connection possibility	DoorLock AccessManager (ART: KXP-2-RS)
Configuration	About KentixONE
RFID Reader 13.56MHz	MIFARE® DESFire® MIFARE® Classic, LEGIC prime LEGIC advant, ISO14443A (CSN / UID) ISO15693 (CSN / UID) Sony FeliCa (CSN / UID) Inside Secure (CSN / UID)

© Kentix GmbH. This file was automatically generated on 2026-10-31 15:01:36. Please visit docs.kentix.com for the latest documentation.

Montage-Schalterprogramm	Für elektr. Schalterprogramme mit Frontausschnitt von 55x55mm
Dimensions	Mit Kunststoffabdeckung (weiss): 80,5 mm x 80,5 mm x 36,5 mm (3,17 x 3,17 x1,44 Zoll) Ohne Kunststoffabdeckung: 71 mm x 71 mm x 30,8 mm (2,80 x 2,80 x 1,22 Zoll)
LED	RED, GREEN, YELLOW
Acoustic signal generator	80dB, 2.3kHz
Sabotage detection	Interne Sabotageerkennung mit Infrarotsensor frontseitig
Connection of wall reader to AccessManager	4-wire cable (cable: J-Y(ST)Y, 4x2x0.8) Cable length up to max. 500m
Addressing	Über AccessManager und Einlernreihenfolge
Communication	2-wire RS485, encrypted (AES128)
Environment	Temperatur -20°C bis +70°C (-13 °F up to +158 °F)
Power supply	24VDC (12-28VDC) via AccessManager
Connection	8-polige Anschlussklemme (X1) lösbar BELEGUNG: (3) DATA-A (4) DATA-B (7) 24VDC (8) GND
Protection class	IP65, reader front
Scope of delivery	Wandleser mit Abdeckrahmen (weiss)
Certification	CE, FCC

© Kentix GmbH. This file was automatically generated on 2026-10-31 15:01:36. Please visit docs.kentix.com for the latest documentation.