

DoorLock-WA6 - Datasheet



ORDER-CODES:
KXC-WA6-IP2

| | |
|-------------------------------|---|
| Function | Wall reader with PIN keypad for surface mounting |
| Connection possibility | DoorLock AccessManager (ART: KXP-2-RS) |
| Configuration | About KentixONE |

| | |
|---|--|
| RFID Reader 13.56MHz | MIFARE® DESFire® MIFARE® Classic, LEGIC prime LEGIC advant, ISO14443A (CSN / UID) ISO15693 (CSN / UID) Sony FeliCa (CSN / UID) Inside Secure (CSN / UID) |
| PIN keypad | Touch PIN keypad with function keys for switching the “armed/disarmed” alarm zone |
| Dimensions | 33 x 131 x 17 mm WxHxD |
| LED | RED, GREEN, YELLOW |
| Acoustic signal generator | 80dB, 2.3kHz |
| Connection of wall reader to AccessManager | 4-wire cable (cable: J-Y(ST)Y, 2x2x0.8) Cable length up to max. 500m |
| Addressing Terminating resistor | Coding switch (default address: 1) ORIENTATION: (1) ADDRESS 1(ON/OFF) (2) ADDRESS 2 (ON/OFF) (3) - (4) - (5) CONSTRUCTION RATE(ON) (6) CONCLUSION RESISTANCE (ON/OFF) |
| Communication | 2-wire RS485, encrypted (AES128) |
| Environment | Temperature -25°C to +60°C |
| Power supply | 10-30VDC, power consumption 1.9W |
| Connection | 4-pin connection terminal detachable CONNECTION: (1) 10-30VDC (2) GND (3) DATA-A (4) DATA-B |
| Protection class | IP66 |
| Scope of delivery | Wall reader with PIN keypad |
| Certification | CE |