

i-PRO Network Camera 5MP with 360° Fish-Eye - MANUAL



ORDER-CODES:
[KWVS4556L](#)

360° dome network camera for integration into KentixONE. The camera can be easily assigned to alarm zones or doors in KentixONE. The camera delivers images with Full HD up to 5MP resolution. With its 360° view, the camera is ideal for monitoring IT and technical rooms, storage rooms and business premises both indoors and outdoors. Especially under dark lighting conditions, almost all crucial image details are captured thanks to the integrated LED infrared illuminators. Thanks to the ONVIF standard, it can also be integrated into video management systems.

[Manual-KWVS4576L_enDownload](#)
[Datasheet-KWV-S4556LDownload](#)

Camera integration in KentixONE

Camera API commands

[IP-Adresse der Kamera] /cgi-bin/camera?[resolution=][&stream=][&ch=]

[Method] GET, [Access level] 3

Parameter name	Value	Comments
resolution	640, 320, 1280, 2048 800, 1600 2560 3072 1920 3840 2192 2992	<p>Resolution to be set (4:3) 640 : VGA 320 : QVGA 1280 : 1280 x 960 2048 : 2048 x 1536 800 800 x 600 1600: 1600x1200 2560: 2560x1920 072: 3072x2304</p> <p>Resolution to be set (16:9) 640 : 640 x 360 320 : 320 x 180 1280 : 1280 x 720 1920 : 1920 x 1080 2048 : 1920 x 1080 2560: 2560x1440 3072: 3072x1728 3840: 3840x2160</p> <p>Resolution to set (1:1) 640 : 640 x 640 320 : 320 x 320 1280 : 1280 x 1280 2192 : 2192 x 2192 2992 : 2992 x 2992</p> <p>When requested resolution is not set for JPEG(1), JPEG(2) or JPEG(3) on camera, camera transmit JPEG(1). #This parameter can be omitted. (Default: JPEG(1))</p>
stream	1, 2,3	<p>Specify the JPEG stream. This parameter can be used instead of the parameter 'resolution'. 1 :JPEG(1) , 2 :JPEG(2) ,3 :JPEG(3) #This parameter can be omitted. (Default: 1)</p>

ch	1, 2, 3, 4	Channel 1: Channel 1 ,2: Channel 2 ,3: Channel 3 .4: Channel 4 #This parameter is supported by Multi-sensor models. When this parameter is omitted, it works as a channel 1
----	------------	--

Example Request JPEG image as single image

Get image in 640x480px resolution:

http://192.168.0.10/cgi-bin/camera?resolution=640

Retrieve image in 1280px resolution from stream 2 of the camera:

http://192.168.0.10/cgi-bin/camera?resolution=1280?stream=2

Protokoll
HTTPS

Wählen Sie hier das Protokoll für die Abfrage der Kamera aus.

Adresse*

10.15.100.202

Die IP-Adresse oder der Hostname der Kamera.

Snapshot-URL

/cgi-bin/camera?resolution=1280?stream=2

Geben Sie hier den Pfad und die Parameter ein, um Bilder der Kamera abzurufen.

Benutzername

admin

Geben Sie hier den Benutzernamen ein, wenn die Kamera durch eine Basic-Authentifizieru...

Passwort

.....

Geben Sie hier das Passwort ein, wenn die Kamera durch eine Basic-Authentifizierung ges...

Verbindung prüfen

KentixONE settings video display

A JPEG with the requested resolution is returned if the requested resolution and the set JPEG resolution match.