

The compatibility of the firmware depends on the date of manufacture of the devices.

Kentix ONE 8.x

For current devices, the latest version of Kentix ONE (versions from 8.x.x) is available on the download page.

Pay attention to the serial number of the device and the production date contained therein:

12**ab**4567**xy**890

The digits a and b stand for the year of production, whereby the numbers are rotated.

Example:

a=1, **b=2**

12 rotated results in 21

This device is from the year 2021.

The same applies to **x** and **y**.

Example:

x=1, **y=0**

Results in 10, rotated= 01.

This device was therefore produced in January 2021.

Compatible with Kentix ONE are

Access Manager

KXP-16-LAN: from 07/2018

MultiSensors

KMS-LAN: from 01/2018

KMS-LAN-RF: from 01/2018

Alarm Manager Basic and Pro

KAM: from 01/2018

Wall readers and DoorLocks are always compatible.

If the AccessManager used for control is not compatible, these devices can continue to be operated on the latest generation of hardware.

When selecting replacement devices for AccessManager radio, the compatible radio technology must be taken into account (radio or BLE).

The KKPT-Touch keypad is no longer supported in Kentix ONE. WallReaders KXC-WAx in combination with an [AccessManager](#) are possible replacements.

Versions 6 and 7

All devices that were not delivered with versions lower than 6.x are compatible with these versions.

From 2024, the connection to Kentix ONE GO or Kentix 360 offered in these versions will no longer be supported. In order to continue using the service, the devices must be updated to Kentix ONE (versions 8.x).

Versions 5 and older

Devices with these software versions cannot be updated to newer versions.

The installation of this software on Kentix devices is the responsibility of the user. The software corresponds to the final scope of functions at the time of publication. There is no further development or maintenance of the software and hardware on this platform. Kentix does not assume any warranty for the function.

The following firmware versions are available for these devices:

KAM-PRO-BASiC V1 (ControlCenter):

https://transfer.kentix.com/legacy/KAM-PRO_05_71_00.zip

KMS-LAN/LAN-RF V1:

https://transfer.kentix.com/legacy/KMS-LAN_05_63_02.zip

KMS-RACK:

https://transfer.kentix.com/legacy/KMS-RACK_05_61_00.zip

KXP-2-RS 2.04.01:

https://transfer.kentix.com/legacy/KentixDoorLock-KXC-WA3_02_04_01.zip

KXP-16-RF 2.04.01 (V1+V2):

https://transfer.kentix.com/legacy/KentixDoorLock-KXP-16_02_04_01.zip

KXP-16-RF 7.01.02 (V1+V2):

https://transfer.kentix.com/legacy/KentixDoorLock-KXP-16_07_01_02.zip